
DCN-MR Meeting recorder software

www.boschsecurity.com





- ▶ Recording in PCM/WAV, WMA or MP3 audio format
- Stereo track can be used for bilingual recording
- Ability to attach speaker names in the audio file
- Network sharing of audio files

The Meeting Recorder can be used in combination with CCS 900, DCN Next Generation or DCN Wireless systems.

The DCN-MR Meeting Recorder software is designed for recording and playback purposes during a meeting or conference.

Recording is done on the hard drive of a computer in PCM/WAV, WMA or MP3 format.

Functions

Recording

The Meeting Recorder can record two analog audio channels. In most cases one audio channel is sufficient to record the floor language. However, in some (bilingual) applications it is ideal to record two channels simultaneously.

Attach speaker names

The name of the current speaker can be attached in the audio file, during or after the meeting. This can be done manually or automatically. Manually by simply double clicking on the delegates name in list. Automatically when the DCN-MR is coupled with the DCN Central Control Unit². For automatic attaching of the speaker names, the delegate names must be assigned to the corresponding microphone numbers. Additional conference information, such as the agenda or meeting minutes can also included in the audio file. ² Open interface LBB 4187/00 or streaming meeting data DCN-SWSMD additional required

Playback

Recorded files can be played back for listening or transcribing. While the audio file is played the name of the speaker (if available) and time-information can be displayed in a window of the text editor. In case two audio sources are recorded, they are recorded as one stereo file. When the balance slider is in the far left position (or right), only the left (or right) channel is heard during playback. When the balance slider is in middle position both audio channels are heard (stereo) making this product ideal for interpreter training applications.

Transcription

Although transcription is possible through the Meeting Recorder, the optional DCN Transcription Module (DCN-MRT) is especially suited for it. The DCN-MRT is in fact the same software as the DCN-MR but without the recording function.

For easy control during transcription; start, stop, fast-forward/rewind, an optional transcription foot pedal is available (DCN-MRFP).

Ease of use

Although it offers many powerful features, the software is easy to use. The intuitive graphic user interface is divided into recording, playback, visualization and files sections.

Installation/configuration notes

Installation

The DCN-MR Meeting Recorder software is supplied on DVD and can be installed on one or more computers.

The software is designed to be used on a computer network. This gives the possibility, for example, to install a Meeting Recorder next to the DCN CCU, while storage of the files is done in parallel on a server via the computer network. Persons responsible for transcription can have access from their computer via the network to the files on the server.

Licence

Licensing of the Meeting Recorder is done with USB dongle. The Meeting Recorder software can be installed on more computers. As soon the USB dongle is plugged-in, the software is ready to use with the applicable licenses. This makes it very flexible, with a minimum of effort and cost.

For demonstration purposes, the DCN-MR software can be used to make or play recordings of five minutes maximum without the dongle.

Parts included Quantity Component

1	DCN-MR Meeting Recorder software on DVD
1	USB dongle (blue)

Technical specifications

Recording formats	(max. sample rate)
	WMA (128 kbps)
	PCM / WAV (48 kHz)
	MP3 (256 kbps)
System platform	Windows 7 Home Premium (32 and 64 bits) or above or Windows Vista Home Premium(32 or 64 bits) or above

Ordering information

DCN-MR Meeting recorder software

DCN Next Generation meeting recorder application. Order number **DCN-MR**

Accessories

DCN-MRT Meeting recorder transcription SW module DCN Next Generation meeting recorder transcription module. To be used with DCN-MR or CCS-CURD. Order number **DCN-MRT**

DCN-MRFP Foot pedal for DCN-MR

DCN Next Generation meeting recorder transcription foot pedal. To be used with DCN-MR or DCN-MRT. Order number **DCN-MRFP**

Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 emea.soccuritysystems@bosch.com emea.boschsecurity.com Germany: Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com North America: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 onlinehelp@us.bosch.com www.boschsecurity.us

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2809 apr.security.systems@bosch.com www.boschsecurity.asia

@ Bosch Security Systems 2019 | Data subject to change without notice 1807011595 | en, V6, 01. Oct 2019