FMM-100DAT2CK-B Manual station, double-action, blue

www.boschsecurity.com





- Terminal connections
- ▶ Gold-plated alarm contacts for corrosion resistance
- Surface back box

The FMM-100DAT2CK-B is a high-quality, metal manual station in blue. This dual-action manual station comes with a key lock and contains gold-plated contacts to resist corrosion.

Functions

Operation

With the dual-action configuration the upper bar on the front of the manual station rotates inward allowing the activation bar to be grasped and operated by a single hand. When the lower bar on the front of the manual station (the activation bar) is pulled, it latches open and is easily visible from 50 ft (15 m). Reset the activation bar by opening the manual station with the key and placing the activation bar in its normal upright position. An optional scored acrylic break rod is available.

Certifications and approvals

Region	Regulatory compliance/quality marks	
USA	UL	UNIU: Boxes, Non-Coded (UL38), UNIU7: Boxes, Non-Coded Certified for Canada (cULus)

Installation/configuration notes

Compatibility Information

The manual station is compatible with all Bosch Security Systems, Inc. Fire Alarm Control Panels.

Mounting Considerations

The manual station can be surface mounted on the FMM-100BB-B Surface-mount Back Box (blue) or flush mounted on a standard single-gang back box. To comply with ADA standards, the manual station must be less than 48 in. (1.2 m) above the floor for front wheelchair access and less than 54 in. (1.3 m) above the floor for side wheelchair access.

This product can expose you to chemicals including lead, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to: www.P65Warnings.ca.gov.

Parts included

The following parts are provided with each manual station in the FMM-100 series:

Quantity	Component
1	Manual station
1	D102 Key (1358 key)
1	FMM-100GR Acrylic Break Rod
1	Hardware pack
1	Literature pack

Technical specifications

Environmental

Relative Humidity:	90% at +100°F (+38°C)
Temperature (operating):	-40°F to +150°F (-40°C to +66°C)

Mechanical

Color:	Blue
Dimensions (H x W x D):	4.75 in. x 3.25 in. x 1.1 in. (12 cm x 8.3 cm x 2.8 cm)
Material:	die-cast metal

Inputs

Switch Rating:

g: 1 A at 30 VDC or 125 VAC

Ordering information

FMM-100DAT2CK-B Manual station, double-action, blue

High-quality, metal manual emergency station in blue Order number **FMM-100DAT2CK-B**

Accessories

D102 Replacement key for D101 lock set

The D102 is a replacement key for locks stamped with 1358.

Order number **D102**

FMM-100BB-B Surface backbox, 4.74x3.25x2.25", blue

Blue cast-metal back box Order number **FMM-100BB-B**

FMM-100GR Break rods, scored acrylic, 12pcs Scored acrylic rods (12 per package) Order number FMM-100GR

Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 emea.soccuritysystems@bosch.com emea.boschsecurity.com Germany: Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com North America: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 onlinehelp@us.bosch.com www.boschsecurity.us

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2809 apr.security.systems@bosch.com www.boschsecurity.asia

© Bosch Security Systems 2019 | Data subject to change without notice 2708873483 | en, V3, 04. Sep 2019